# G+H Electrical Accessories

## Technical Datasheet

**Description:** Georgian Black Bronze Cooker Switch with Neon

**Part Number:** MBB28B






## Information

| | |
|---|---|
| **Plate Dimensions (mm)** | 94 (W) x 154 (H) x 8 (D) |
| **Insert Material** | Polycarbonate |
| **Earth Strap** | Mild Steel |
| **Operating Voltage(AC)** | 250V @ 50Hz |
| **Termination Type** | Screw |
| **Warranty** | 10 years |
| **Product Class 1** | Must be earthed |
| **Maintenance** | Clean with a soft cloth only. Do not use a cleaning agent of any description. |
| **Please Note** | Do not use masking tape on this product. |
| **Style** | Stepped Profile with Rope edge |
| **Plate Material** | Solid Brass, Hand-finished, Lacquered |
| **Switch Material** | Metal |
| **Required back box depth** | 47mm |
| **Load Rating** | 45A |
| **Switch type** | Double pole |
| **Terminal Capacity** | 4x 4.0mm² ,3x 6.0mm², 1x 16.0mm²(L&N) / 3x 2.5mm² ,2x 4.0mm², 1x 6.0mm²(EARTH) |
| **Standards** | BS EN 60669-1, BS 4177(sockets) |
| **IP Rating** | IP2XD |

Tel: 01905 888283 Email: info@gandhelectrical.co.uk
G+H Electrical Accessories | Unit N4 | Blackpole East | Blackpole Road | Worcester | WR3 8SG
Registered in England and Wales.Company number: 7944793 | VAT registration number: 641034480
Â©2021 - 2025 G & H Brassware Ltd. All rights reserved.